

1 RELAY DECODER

Description:

- DCC accessory decoder with a relay output
- max output current: 230V/3A
- on-board programming button
- can be used for switching house or street lights, polarize frog, supply a hidden track, or control a 2-aspect light
- the relay position is saved in the internal memory (remember it when the power is switched off)
- the module is suitable for controlling a polarized frog. The address can be the same as the turnout decoder

Programming:

- press the programming button 4 times, the LED starts flashing, and the relay clicks
- enter the address on your hand controller and let it move as an accessory
- if you want to swap the on/off button, repeat the programming once again

Program button



DCC Relay output